



Surface Mount Rectifier Markings

Cathode Band
(not included on bidirectional TVS)

Device Marking

Rectron Logo
(only on SMC)

Factory Date Code

Factory Date Code "XYZZ": "X" = Factory code, "Y" = Last digit of year, From 2010, the code should be 2010 : A/ 2011 : B/ 2012 : C....., "ZZ" = MFG week

Examples

Part No.	FFM101	FFM102	FFM103	FFM104	FFM105	FFM106	FFM107
Marking	F1	F2	F3	F4	F5	F6	F7

Factory Date Code: "V343" : 2003, 43rd week; "V221" : 2002, 21st week

Device Markings

SMA

Part number	Device Marking	Part number	Device Marking
FFM101 to FFM107	F1 to F7	HFM101 to HFM108	H1 to H8
FM4001 to FM4007	A1 to A7	EFM101 to EFM106	E1 to E6
FM4933 to FM4937	R3 to R7	FM120 to FM1100	S2 to S10
FM5817 to FM5819	K7 to K9		
P4FMAJ6.8 to P4FMAJ170CA	AP6.8 to AP170CA	TFMAJ6.8 to TFMAJ170CA	TA6.8 to TA170CA

SMB

Part number	Device Marking	Part number	Device Marking
FFM201 to FFM207	2F1 to 2F7	HFM201 to HFM208	2H1 to 2H8
FM201 to FM207	2B1 to 2B7	EFM201 to EFM206	2E1 to 2E6
FM220 to FM2100	2S2 to 2S10		
P6FMBJ6.8 to P6FMBJ170CA	BP6.8 to BP170CA	TFMBJ6.8 to TFMBJ170CA	TB6.8 to TB170CA



Device Markings

SMC

Part number	Device Marking	Part number	Device Marking
FFM301 to FFM307	3F1 to 3F7	HFM301 to HFM308	3H1 to 3H8
FM301 to FM307	3C1 to 3C7	EFM301 to EFM306	3E1 to 3E6
FM5820 to FM5822	K0 to K2	FM320 to FM3100	3S2 to 3S10
1.5FMCJ6.8 to 1.5FMCJ170CA	CP6.8 to CP170CA	TFMCJ6.8 to TFMCJ170CA	TC6.8 to TC170CA

SMX

Part number	Device Marking	Part number	Device Marking
FFM101W to FFM107W	F1 to F7	HFM101W to HFM108W	H1 to H8
FM4001W to FM4007W	A1 to A7	FM4933W to FM4937W	R3 to R7